


A MATHEMATICAL DESCRIPTION OF THE STATION ALERT
PREDICTOR(U) NAVAL SURFACE WEAPONS CENTER DAHLGREN VA
A D PARKS SEP 82 NSWC/TR-82-387

UNCLASSIFIED

F/G 22/3


NL

	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100	101	102	103	104	105	106	107	108	109	110	111	112	113	114	115	116	117	118	119	120	121	122	123	124	125	126	127	128	129	130	131	132	133	134	135	136	137	138	139	140	141	142	143	144	145	146	147	148	149	150	151	152	153	154	155	156	157	158	159	160	161	162	163	164	165	166	167	168	169	170	171	172	173	174	175	176	177	178	179	180	181	182	183	184	185	186	187	188	189	190	191	192	193	194	195	196	197	198	199	200	201	202	203	204	205	206	207	208	209	210	211	212	213	214	215	216	217	218	219	220	221	222	223	224	225	226	227	228	229	230	231	232	233	234	235	236	237	238	239	240	241	242	243	244	245	246	247	248	249	250	251	252	253	254	255	256	257	258	259	260	261	262	263	264	265	266	267	268	269	270	271	272	273	274	275	276	277	278	279	280	281	282	283	284	285	286	287	288	289	290	291	292	293	294	295	296	297	298	299	300	301	302	303	304	305	306	307	308	309	310	311	312	313	314	315	316	317	318	319	320	321	322	323	324	325	326	327	328	329	330	331	332	333	334	335	336	337	338	339	340	341	342	343	344	345	346	347	348	349	350	351	352	353	354	355	356	357	358	359	360	361	362	363	364	365	366	367	368	369	370	371	372	373	374	375	376	377	378	379	380	381	382	383	384	385	386	387	388	389	390	391	392	393	394	395	396	397	398	399	400	401	402	403	404	405	406	407	408	409	410	411	412	413	414	415	416	417	418	419	420	421	422	423	424	425	426	427	428	429	430	431	432	433	434	435	436	437	438	439	440	441	442	443	444	445	446	447	448	449	450	451	452	453	454	455	456	457	458	459	460	461	462	463	464	465	466	467	468	469	470	471	472	473	474	475	476	477	478	479	480	481	482	483	484	485	486	487	488	489	490	491	492	493	494	495	496	497	498	499	500	501	502	503	504	505	506	507	508	509	510	511	512	513	514	515	516	517	518	519	520	521	522	523	52
--	---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	----



MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS-1963-A

TR 82-387



UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER NSWC TR 82-387	2. GOVT ACCESSION NO. AD-A158021	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) A MATHEMATICAL DESCRIPTION OF THE STATION ALERT PREDICTOR	5. TYPE OF REPORT & PERIOD COVERED Final	
7. AUTHOR(s) A. D. PARKS	6. PERFORMING ORG. REPORT NUMBER	
9. PERFORMING ORGANIZATION NAME AND ADDRESS Naval Surface Weapons Center (K13) Dahlgren, VA 22448	8. CONTRACT OR GRANT NUMBER(s)	
11. CONTROLLING OFFICE NAME AND ADDRESS Defense Mapping Agency Washington, DC 20370	10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS 63701B	
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office)	12. REPORT DATE September 1982	
	13. NUMBER OF PAGES 40	
	15. SECURITY CLASS. (of this report) UNCLASSIFIED	
	15a. DECLASSIFICATION/DOWNGRADING SCHEDULE	
16. DISTRIBUTION STATEMENT (of this Report) Approved for public release; distribution unlimited.		
17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)		
18. SUPPLEMENTARY NOTES		
19. KEY WORDS (Continue on reverse side if necessary and identify by block number) Ground station alert predictor; mathematical description Alert predictor Satellite tracking station		
20. ABSTRACT (Continue on reverse side if necessary and identify by block number) A functional and mathematical description of the ground station alert predictor is presented. The alert predictor generates the times during which a satellite will be visible to a ground tracking station and provides ground antenna pointing information. The methods used to generate this information are computationally quite efficient so that long-term predictions can be done rapidly. Several new innovations are included in the algorithms: the effects of atmospheric drag upon satellites are taken into account, (continued on back)		

DD FORM 1 JAN 73 1473

EDITION OF 1 NOV 65 IS OBSOLETE
S/N 0102-LF-014-6601

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

Block 20 continued.

and a satellite orbit adjust may be included during the prediction interval.

UNCLASSIFIED

SECURITY CLASSIFICATION OF THIS PAGE (When Data Entered)

FOREWORD

This report presents a functional and mathematical description of the ground station alert predictor. The alert predictor generates the times during which a satellite will be visible to a ground tracking station and provides ground antenna pointing information. This is an invaluable tool that is useful for scheduling ground station operational activities. The methods used to generate this information are computationally quite efficient so that long-term predictions can be done rapidly. Several new innovations are included in the algorithms: the effects of atmospheric drag upon satellites are taken into account, and a satellite orbit adjust may be included during the prediction interval.

Released by:

O. F. Braxton

O. F. BRAXTON, Head

Strategic Systems Department



Approved	
1.000 0.001	<input checked="" type="checkbox"/>
1.000 1.000	<input type="checkbox"/>
Unannounced	<input type="checkbox"/>
Justification	
By	
Distribution/	
Availability Codes	
Dist	Avail and/or Special
A-1	

CONTENTS

<u>Section</u>		<u>Page</u>
1.0	Introduction	1
2.0	The Process Flow Supervisor (PFS)	3
2.1	Functional Description	3
2.2	Special Features	6
2.3	Processing Equations	7
3.0	The Station-Satellite Inview Predictor (SIP)	8
3.1	Functional Description	8
3.2	Processing Equations.	10
3.3	Inview Geometry Parameter Computations	12
4.0	The Brouwer Orbit Generator (BOG)	15
4.1	Functional Description	15
4.2	Processing Equations for the Brouwer-Lyddane Method .	17
4.3	Processing Equations for the Keplerian Update Method .	24
4.4	Processing Equations for Transforming Orbital Elements to Cartesian Coordinates	24
5.0	The Brouwer Mean Element Converter (BMC)	27
5.1	Functional Description	27
5.2	Processing Equations.	27

ILLUSTRATIONS

<u>Figure</u>		<u>Page</u>
1-1	ALERT Functional Overview and Data Flow	2
2-1	Process Flow Supervisor Logic Flow.	4
3-1	Station-Satellite Inview Predictor Process Flow	9
4-1	Brouwer Orbit Generator Process Flow	16
5-1	Process Flow of the Brouwer Mean Element Converter . . .	26

SECTION 1

INTRODUCTION

The primary function of the ALERT package is to predict the times during which a satellite will be visible at a ground tracking station and provide approximate ground antenna pointing information. The methods used to generate this information are computationally quite efficient, so that the in-view times and associated information for a given satellite and ground station can be rapidly predicted for fairly long prediction intervals (~30 days). An additional optional feature exists which accounts for the inclusion of a satellite orbit adjust during the prediction interval.

A functional overview of the ALERT generator is shown in Figure 1-1. As can be seen from this figure, the ALERT generator is comprised of four basic computational functions: the process flow supervisor (PFS), the Brouwer mean element converter (BMC), the satellite-station in-view predictor (SIP), and the Brouwer orbit generator (BOG). Also shown on this figure is the inter-function data flow. A detailed description of each of these functions is presented in the following sections.

As user supplied input, the ALERT generator requires the station and satellite and associated frequency information for which in-view periods are to be predicted, as well as the start (t_B) and stop (t_E) times of the time interval over which predictions are to be made. Also included in the input is the option selected by the user for the inclusion of the impact of orbit adjusts occurring during the prediction interval on in-view periods. In order to initiate its processing the ALERT generator requires the following additional data as shown on Figure 1-1: station latitude, longitude, and height; mean Brouwer elements and decay rates; and post orbit adjust epoch, inertial position and velocity vectors if the effect of an orbit adjust is to be included in the prediction span. The predicted inview periods and associated station antenna pointing geometry that were computed for the prediction interval are written to hardcopy at the end of the computational cycle.




FIGURE 1-1. ALERT FUNCTIONAL OVERVIEW END DATA FLOW

SECTION 2

THE PROCESS FLOW SUPERVISOR (PFS)

2.1 FUNCTIONAL DESCRIPTION

The principal tasks performed by the PFS are to receive and retrieve data, direct processing flow, and output computed results. Specifically the PFS function:

- (i) receives input data;
- (ii) retrieves station coordinates;
- (iii) retrieves initial SPASUR Brouwer mean elements and decay rates;
- (iv) receives predicted orbit adjust times and post adjust vectors;
- (v) cycles computations through BMC if required;
- (vi) cycles computations through SIP; and
- (vii) receives SIP predictions and outputs them.

The flow of the PFS function is presented in Figure 2-1.

It should be noted that tasks (iv) and (v) above are optional. Should the user elect to use one of the two orbit adjust options and an orbit adjust falls within the prediction span, the PFS retrieves the predicted orbit adjust time (t_{OA}) and the associated predicted post adjust position and velocity at a time t'_{OA} very near (but later than) t_{OA} , $\vec{r}(t'_{OA})$ and $\dot{\vec{r}}(t'_{OA})$. These osculating Cartesian vectors are passed to the BMC function where they are converted to Brouwer mean elements for the time t'_{OA} .

As noted above, the orbit adjust option can operate in two modes. If the orbit adjust option flag IOAOP is set to zero, the option is not used and SIP predictions are generated using only the initial element set obtained from the SPASUR data. However, if it is set to one or two, the retrieval and conversion of the post adjust vectors take place, as described above. When IOAOP is set to one, the prediction span is divided into two partitions using t'_{OA} as the boundary, and the initial Brouwer elements retrieved




FIGURE 2-1. PROCESS FLOW SUPERVISOR LOGIC FLOW




FIGURE 2-1. PROCESS FLOW SUPERVISOR LOGIC FLOW (CONTINUED)

2.1 FUNCTIONAL DESCRIPTION (con't)

by the PFS from the SPASUR element data are used for SIP in-view predictions until t'_{OA} is reached. For times later than t'_{OA} the post-orbit adjust Brouwer mean elements generated by the BMC function are used for SIP predictions. When IOAOP is set to two, SIP predictions are generated only for times later than t'_{OA} using the Brouwer element set generated by the BMC function.

2.2 SPECIAL FEATURES

Several points associated with the orbit adjust option are worthy of note. First, the orbit adjust options ($IOAOP \neq 0$) may be selected only for those satellites which are supported by the PULSAR system¹. If the option has been selected for a satellite other than those, the option is denied and processing continues as if the option had never been selected. Secondly, if the orbit adjust option has been validly selected, the PFS uses the decay rates obtained from the SPASUR element file for the epoch t'_B as the decay rates for times later than t'_{OA} .

The epoch t'_B above corresponds to the time of the Brouwer mean element set obtained from the SPASUR data nearest, but not later than, the start time of the prediction interval t_B , i.e. $t'_B \leq t_B$. If an orbit adjust occurs within the time interval between t'_B and t_B processing is still performed as described above. However, the alert schedule only for the time interval $[t_B, t_E]$ will be output.

¹ Parks, A.D. and Hicks, T.I., A Mathematical Description of the PULSAR Doppler Tracking Data Editor, NSWC/DL TR 82-391, Dahlgren, Virginia, 1982.

2.3 PROCESSING EQUATIONS

The semi-major axis read from the SPASUR data is the Kaula semi-major axis a_k expressed in earth radii. This is converted in the PFS to the Brouwer mean semi-major axis a'' via the transformation

$$a'' = a_k a_e \left(\frac{1 + 2X}{1 - X} \right)^{2/3}, \quad (2.1)$$

where

$$X = \frac{3J_2(1 - 3/2 \sin^2 i'')}{4 a_k^2 (1 - e''^2)^{3/2}}. \quad (2.2)$$

In the above expressions a_e is the earth's semi-major axis; J_2 is a zonal harmonic gravitational constant; and i'' and e'' are the Brouwer mean inclination and eccentricity, respectively.

Similarly, the semi-major axis decay rate obtained from the SPASUR data is the time rate of change of the Kaula semi-major axis \dot{a}_k . This is converted in PFS to the time rate of change of the Brouwer mean semi-major axis \dot{a}'' through application of the expression

$$\dot{a}'' = \dot{a}_k a_e \left(\frac{1 + 2X}{1 - X} \right)^{2/3} + 2 a_k a_e \dot{X} \left[(1 + 2X)(1 - X)^5 \right]^{1/3}, \quad (2.3)$$

where

$$\dot{X} = X \left[3 \left(\frac{e''}{1 - e''^2} \right) \dot{e}'' - 2 \left(\frac{\dot{a}_k}{a_k} \right) \right]. \quad (2.4)$$

In the last expression it has been assumed that

$$(\dot{i}'') = 0. \quad (2.5)$$

Values for \dot{e}'' and the rate of change of the mean motion \dot{n} are also obtained from the SPASUR data.

SECTION 3

THE STATION-SATELLITE INVIEW PREDICTOR (SIP)

3.1 FUNCTIONAL DESCRIPTION²

The station-satellite in-view times can be obtained by considering the vertical distance Δ of the satellite above a horizontal plane tangent to the earth at the station's location. An inview period is considered to begin or end when the satellite is in the horizontal station plane, i.e., when $\Delta = 0$. Since the earth rotates, the satellite will dip below the zero level and may not appear above the horizontal plane for many revolutions.

To initiate SIP processing, it must first be determined where the satellite is at time t_B with respect to the maximum points of the function describing Δ . Once this is done, the first maximum is approached in fractional parts of a satellite period P until a close proximity of the maximum Δ is reached. This is accomplished by using the signs and magnitudes of the Δ and its first and second time derivatives, Δ' and Δ'' , to determine how far to step forward in time. When the maximum Δ has been approached sufficiently close, and it is greater than zero, the exact time of maximum Δ is obtained iteratively. This time is used to compute approximate rise and set times, which are then refined using an iterative method. This procedure is repeated to find successive maximum Δ s and associated rise and set times until the end of the prediction interval t_E is exceeded.

For each in-view period geometric parameters are computed and stored. When the end of the prediction interval is exceeded, the in-view times and associated geometry computations are passed to the PFS for output. The process flow of SIP is presented in Figure 3-1.

² Castro, H.E., A New Method for Finding Station Prediction Alerts, NSWC/DL TM K-1/63, Dahlgren, Virginia, 1963.




FIGURE 3-1. STATION-SATELLITE IN-VIEW PREDICTOR PROCESS FLOW

3.2 PROCESSING EQUATIONS

The orbital period P is computed using

$$P = \frac{2\pi}{\mu^{1/2}} a^{3/2} \quad (3.1)$$

where μ is the gravitational constant and a the semi-major axis.

The vertical distance Δ of a satellite from a horizontal plane tangent at a station location is given by:

$$\Delta = \cos\phi (\chi \cos\alpha + y \sin\alpha) + z \sin\phi - R_0, \quad (3.2)$$

where

$$\alpha = \omega(t - t_{ve}) + \lambda,$$

$$R_0 = a_e (1 - \epsilon^2 \sin^2\phi)^{1/2} + h,$$

$$\phi = \text{station geodetic latitude,}$$

$$\lambda = \text{station longitude,}$$

$$\omega = \text{earth's rotation rate,}$$

$$a_e = \text{earth's equatorial radius,}$$

$$t_{ve} = \text{universal time of transit of vernal equinox,}$$

$$\epsilon = \text{eccentricity of earth,}$$

$$x, y, z = \text{satellite inertial position components, and}$$

$$h = \text{height of station above reference ellipsoid.}$$

3.2 PROCESSING EQUATIONS (con't)

The first and second time derivatives of Δ are given by

$$\Delta' = \cos \phi \left[(\dot{y} - \omega x) \sin \alpha + (\dot{x} + \omega y) \cos \alpha \right] + \dot{z} \sin \phi, \quad (3.3)$$

and

$$\Delta'' = \cos \phi \left[(\ddot{y} - 2\omega \dot{x} + \omega^2 y) \sin \alpha + (\ddot{x} + 2\omega \dot{y} - \omega^2 x) \cos \alpha \right] + \ddot{z} \sin \phi, \quad (3.4)$$

where

$\dot{x}, \dot{y}, \dot{z}$ = satellite inertial velocity components,

$$\ddot{x} = -\mu \frac{x}{r^3},$$

$$\ddot{y} = -\mu \frac{y}{r^3}, \text{ and}$$

$$\ddot{z} = -\mu \frac{z}{r^3}.$$

The expression required for the iterative solution for the time of maximum Δ , i.e. t_m , is given by

$$t_m^{(i+1)} = t_m^{(i)} - \frac{\Delta'(t_m^{(i)})}{\Delta''(t_m^{(i)})}, \quad (3.5)$$

where the superscripts in parentheses indicate t_m s obtained from the i^{th} iteration. Equation (3.5) is assumed to have converged when the tolerance condition

$$|t_m^{(i+1)} - t_m^{(i)}| < \tau_1, \quad (3.6)$$

3.2 PROCESSING EQUATIONS (con't)

is satisfied. The first estimate of t_m to be used in equation (3.5) for $t_m^{(0)}$ is the value of t obtained prior to entering the A section of logic in Figure 3-1.

First estimates of the rise time t_r and set time t_s associated with the time of maximum Δ , t_m , are given by

$$t_r = t_m - \sqrt{\frac{-2\Delta}{\Delta''}} \quad \text{and} \quad t_s = t_m + \sqrt{\frac{-2\Delta}{\Delta''}} \quad (3.7)$$

These estimates are used to initiate iterative solutions for more exact rise and set times using equation (3.5). Convergence is assumed to have occurred when equation (3.6) is satisfied for both t_r and t_s .

3.3 IN-VIEW GEOMETRY PARAMETER COMPUTATIONS

The time of maximum Δ , i.e., t_m , is used to initiate the iterative solution for the time of closest approach t_{CA} , via the following expression:

$$t_{CA}^{(i+1)} = t_{CA}^{(i)} - \left(\frac{A}{\dot{A} - \frac{A^2}{|\vec{r} - \vec{r}_0|^2}} \right) \quad , \quad t = t_{CA}^{(i)} \quad (3.8)$$

where

$$A = (x - a_1 \cos \alpha) (\dot{x} + a_1 \omega \sin \alpha) + (y - a_1 \sin \alpha) (\dot{y} - a_1 \omega \cos \alpha) + (z - b_1) \dot{z} \quad (3.9)$$

$$\dot{A} = (x - a_1 \cos \alpha) (\ddot{x} + a_1 \omega^2 \cos \alpha) + (\dot{x} + a_1 \omega \sin \alpha)^2 + (y - a_1 \sin \alpha) (\ddot{y} + a_1 \omega^2 \sin \alpha) + (\dot{y} - a_1 \omega \cos \alpha)^2 + (z - b_1) \ddot{z} + \dot{z}^2 \quad (3.10)$$

$$|\vec{r} - \vec{r}_0|^2 = (x - a_1 \cos \alpha)^2 + (y - a_1 \sin \alpha)^2 + (z - b_1)^2 \quad (3.11)$$

3.2 PROCESSING EQUATIONS (con't)

$$a_1 = \left[a_e (1 - \epsilon^2 \sin^2 \phi)^{-\frac{1}{2}} + h \right] \cos \phi, \quad (3.12)$$

and

$$b_1 = \left[a_e (1 - \epsilon^2) (1 - \epsilon^2 \sin^2 \phi)^{-\frac{1}{2}} + h \right] \sin \phi. \quad (3.13)$$

The azimuths A at t_r , t_{CA} , and t_s are computed using the equation:

$$A = \tan^{-1} \left\{ \frac{-(x \sin \alpha - y \cos \alpha)}{-\sin \phi (x \cos \alpha + y \sin \alpha) + \cos \phi \left[(z + a_e \epsilon^2 \sin \phi) / (1 - \epsilon^2 \sin^2 \phi)^{\frac{1}{2}} \right]} \right\}. \quad (3.14)$$

If

$$|x \sin \alpha - y \cos \alpha| < \tau_2 \quad (3.15)$$

and

$$|\sin \phi (x \cos \alpha + y \sin \alpha) - \cos \phi \left[(z + a_e \epsilon^2 \sin \phi) / (1 - \epsilon^2 \sin^2 \phi)^{\frac{1}{2}} \right]| < \tau_2, \quad (3.16)$$

then A is set to zero.

The Doppler frequency Δn (scaled to 100 mc and including the offset frequency) is computed at t_r and t_s using the relation:

$$\begin{aligned} \Delta n = \left(\frac{-f_s}{.2997928} \right) & \left[(x - a_1 \cos \alpha)(\dot{x} + a_1 \omega \sin \alpha) - (y - a_1 \sin \alpha)(\dot{y} - a_1 \omega \cos \alpha) \right. \\ & \left. + (z - b_1)\dot{z} \right] \cdot \left[(x - a_1 \cos \alpha)^2 + (y - a_1 \sin \alpha)^2 \right. \\ & \left. + (z - b_1)^2 \right]^{-\frac{1}{2}} \left(\frac{100}{108} \right) + 100f_{os}, \end{aligned} \quad (3.17)$$

3.2 PROCESSING EQUATIONS (con't)

where f_s is the satellite frequency and f_{os} is the satellite off-set frequency.

The elevation E at t_{CA} is computed using the expression

$$E = \sin^{-1} \frac{\Delta}{|\vec{r} - \vec{r}_0|} \quad , \quad (3.18)$$

and the slant range ρ at t_{CA} is obtained from

$$\rho = [(x - a_1 \cos\alpha)^2 + (y - a_1 \sin\alpha)^2 + (z - b_1)^2]^{1/2} \quad . \quad (3.19)$$

SECTION 4

THE BROUWER ORBIT GENERATOR (BOG)

4.1 FUNCTIONAL DESCRIPTION

The Brouwer orbit generator function is used by the station alert prediction software package to supply predicted inertial position and velocity vectors for the satellite being processed. These vectors are used by the SIP function to generate station-satellite in-view periods. The BOG function is also used by the BMC function to convert osculating inertial Cartesian coordinates to mean Brouwer elements (it is assumed in this case that the satellites for which this is done have inclinations which are not in the neighborhood of the Brouwer-Lyddane singularity at $\sim 63.5^\circ$).

Two methods are available for generating osculating elements in the BOG function. As long as the satellite inclination is not in the neighborhood of 63.5° , the Brouwer-Lyddane^{3,4} theory modified to include drag effects is used to generate predicted osculating elements. If the inclination is sufficiently close to 63.5° , a Keplerian update method using secular terms only and no drag effects is applied to the mean elements. These updated elements are then used as the osculating elements in subsequent SIP calculations. In each case when BOG is being utilized by the SIP function, the osculating elements are transformed to osculating inertial Cartesian coordinates before returning to SIP. If BOG is being used by the BMC functions, no such transformation takes place. The BOG processing flow is shown in Figure 4-1.

³ Brouwer, D., "Solution of the Problem of Artificial Satellite Theory Without Drag", The Astronomical Journal, Vol. 64, No. 1274, 1959, pp. 378 - 397.

⁴ Lyddane, R. H., "Small Eccentricities or Inclinations in the Brouwer Theory of Artificial Satellites", The Astronomical Journal, Vol. 68, No. 8, 1963, pp. 555 - 558.




FIGURE 4-1. BROUWER ORBIT GENERATOR PROCESS FLOW

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD

The equations used to compute osculating orbital elements from mean Brouwer elements and decay rates are delineated in this section. First define the following:

$$\begin{aligned}
 \dot{a}'' &= \text{semi-major axis decay rate} \\
 \dot{e}'' &= \text{eccentricity decay rate} \\
 \dot{n} &= \text{time rate of change of mean motion} \\
 t &= \text{time from epoch} \\
 n_0 &= (\mu/a''^3)^{1/2} \\
 \eta &= (1 - e''^2)^{1/2} \\
 \theta &= \cos i'' \\
 \gamma_2 &= \frac{1}{2} C_{20} a_e^2 / a''^2 \\
 \gamma_2' &= \gamma_2 \eta^{-4} \\
 \gamma_3' &= -C_{30} a_e^3 a''^{-3} \eta^{-6} \\
 \gamma_4' &= -3/8 C_{40} a_e^4 a''^{-4} \eta^{-8} \\
 \gamma_5' &= -C_{50} a_e^5 a''^{-5} \eta^{-10} \\
 \alpha &= 1 - 5\theta^2 \\
 \beta &= 1 - 11\theta^2 - 40\theta^4 \alpha^{-1} \\
 \gamma &= 1 - 3\theta^2 - 8\theta^4 \alpha^{-1} \\
 \delta &= 1 - 9\theta^2 - 24\theta^4 \alpha^{-1} \\
 \lambda &= 1 - 5\theta^2 - 16\theta^4 \alpha^{-1} ,
 \end{aligned} \tag{4.1}$$

where the C_{j0} ($j = 2, 3, 4, 5$) are the zonal harmonic gravitational expansion coefficients. Then the secular terms are computed from:

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD (con't)

$$\begin{aligned} \ell'' = n_0 t \left\{ 1 + \frac{3}{2} \gamma_2' \eta (3\theta^2 - 1) + \frac{3}{32} \gamma_2'^2 \eta \left[-15 + 16\eta + 25\eta^2 \right. \right. \\ \left. \left. + (30 - 96\eta - 90\eta^2)\theta^2 + (105 + 144\eta + 25\eta^2)\theta^4 \right] \right. \\ \left. + \frac{15}{16} \gamma_4' \eta e''^2 \left[3 - 30\theta^2 + 35\theta^4 \right] \right\} + \ell_0'' + \dot{n}_t^2 \end{aligned} \quad (4.2)$$

$$\begin{aligned} g'' = n_0 t \left\{ -\frac{3}{2} \gamma_2' \alpha + \frac{3}{32} \gamma_2'^2 \left[-35 + 24\eta + 25\eta^2 \right. \right. \\ \left. \left. + (90 - 192\eta - 126\eta^2)\theta^2 + (385 + 360\eta + 45\eta^2)\theta^4 \right] \right. \\ \left. + \frac{5}{16} \gamma_4' \left[21 - 9\eta^2 + (-270 + 126\eta^2)\theta^2 + (385 - 189\eta^2)\theta^4 \right] \right\} + g_0'', \end{aligned} \quad (4.3)$$

and

$$\begin{aligned} h'' = n_0 t \left\{ -3\gamma_2' \theta + \frac{3}{8} \gamma_2'^2 \left[(-5 + 12\eta + 9\eta^2)\theta + (-35 - 36\eta - 5\eta^2)\theta^3 \right] \right. \\ \left. + \frac{5}{4} \gamma_4' (5 - 3\eta^2)\theta (3 - 7\theta^2) \right\} + h_0''. \end{aligned} \quad (4.4)$$

The long period (dependent upon g'') terms are computed from:

$$\begin{aligned} \delta_1 e = \frac{35}{96} \frac{\gamma_5'}{\gamma_2'} e''^2 \eta^2 \lambda \sin \epsilon'' \sin^3 g'' - \frac{1}{12} \frac{e'' \eta^2}{\gamma_2'} (3\gamma_2'^2 \beta - 10\gamma_4' \gamma) \sin^2 g'' \\ - \frac{35}{128} \frac{\gamma_5'}{\gamma_2'} e''^2 \eta^2 \lambda \sin \epsilon'' \sin g'' + \frac{1}{4} \frac{\eta^2}{\gamma_2'} \left[\gamma_3' + \frac{5}{16} \gamma_5' (4 + 3e''^2) \delta \right] \\ \sin \epsilon'' \sin g'' + \frac{e'' \eta^2}{24\gamma_2'} \left[3\gamma_2'^2 \beta - 10\gamma_4' \gamma \right] \end{aligned} \quad (4.5)$$

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD (con't)

$$\begin{aligned}
\ell' + g' = & g'' + \ell'' + \frac{1}{2} \left\{ \frac{1}{24\gamma_2'} \left[-3\gamma_2'^2 \left\{ 2 + e''^2 - 11(2 + 3e''^2)\theta^2 \right. \right. \right. \\
& - 40(2 + 5e''^2)\theta^4\alpha^{-1} - 400e''^2\theta^6\alpha^{-2} \left. \right\} \\
& + 10\gamma_4' \left\{ 2 + e''^2 - 3(2 + 3e''^2)\theta^2 - 8(2 + 5e''^2)\theta^4\alpha^{-1} - 80e''^2\theta^6\alpha^{-2} \right\} \left. \right] \\
& + \frac{\eta^3}{\gamma_2'} \left[\frac{\gamma_2'^2}{4} \beta - \frac{5}{6} \gamma_4' \gamma \right] \left\{ \sin 2g'' + \left\{ \frac{35}{384} \frac{\gamma_5'}{\gamma_2'} \eta^3 e'' \lambda \sin \dot{\lambda}'' \right. \right. \\
& + \frac{35}{1152} \frac{\gamma_5'}{\gamma_2'} \left[\lambda \left\{ -e''(3 + 2e''^2) \sin \dot{\lambda}'' + \frac{e''^3 \theta^2}{\sin \dot{\lambda}''} \right\} \right. \\
& + 2e''^3 \theta^2 \sin \dot{\lambda}'' \left. \left\{ 5 + 32\theta^2 \alpha^{-1} + 80\theta^4 \alpha^{-2} \right\} \right] \left. \right\} \cos 3g'' \\
& + \left\{ -\frac{\gamma_3' e'' \theta^2}{4\gamma_2' \sin \dot{\lambda}''} + \frac{5}{64} \frac{\gamma_5'}{\gamma_2'} \left[-e'' \frac{\theta^2}{\sin \dot{\lambda}''} (4 + 3e''^2) + e'' \sin \dot{\lambda}'' \right. \right. \\
& (26 + 9e''^2) \left. \right] \delta - \frac{15}{32} \frac{\gamma_5'}{\gamma_2'} e'' \theta^2 \sin \dot{\lambda}'' (4 + 3e''^2) \\
& (3 + 16\theta^2 \alpha^{-1} + 40\theta^4 \alpha^{-2}) + \frac{1}{4} \frac{\gamma_3'}{\gamma_2'} \sin \dot{\lambda}'' \left. \right\} \\
& \left(\frac{e''}{1+\eta^3} \right) [3 - e''^2 (3 - e''^2)] + \frac{5}{64} \frac{\gamma_5'}{\gamma_2'} \eta^2 \delta \\
& \left[\frac{e''(-32 + 81e''^4)}{4 + 3e''^2 + \eta(4 + 9e''^2)} \right] \sin \dot{\lambda}'' \left. \right\} \cos g''
\end{aligned} \tag{4.6}$$

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD (con't)

and

$$\begin{aligned}
h' = h'' + \frac{35 \gamma_5' e''^3 \theta}{144 \gamma_2'} & \left\{ \frac{1}{2} \lambda \sin^{-1} \dot{\chi}'' + \sin \dot{\chi}'' \left[5 + 32 \theta^2 \alpha^{-1} + 80 \theta^4 \alpha^{-2} \right] \right\} \\
& \sin^2 g'' \cos g'' + \frac{e''^2 \theta}{12 \gamma_2'} \left\{ -3 \gamma_2'^2 \left[11 + 80 \theta^2 \alpha^{-1} + 200 \theta^4 \alpha^{-2} \right] \right. \\
& + 10 \gamma_4' \left[3 + 16 \theta^2 \alpha^{-1} + 40 \theta^4 \alpha^{-2} \right] \left. \right\} \sin g'' \cos g'' \\
& + \left\{ -\frac{35 \gamma_5'}{576 \gamma_2'} e''^3 \theta \left[\frac{1}{2} \lambda \sin^{-1} \dot{\chi}'' + \sin \dot{\chi}'' (5 + 32 \theta^2 \alpha^{-1} + 80 \theta^4 \alpha^{-2}) \right] \right. \\
& + \frac{e'' \theta}{4 \gamma_2' \sin \dot{\chi}''} \left[\gamma_3' + \frac{5}{16} \gamma_5' (4 + 3e''^2) \delta + \frac{15}{8} \gamma_5' (4 + 3e''^2) \right. \\
& \left. \left. (3 + 16 \theta^2 \alpha^{-1} + 40 \theta^4 \alpha^{-2}) \sin^2 \dot{\chi}'' \right] \right\} \cos g'' . \tag{4.7}
\end{aligned}$$

The short periodics (dependent upon E' , δ' , ℓ'') are computed from:

$$\begin{aligned}
a = \dot{a}'' t + a'' - a'' \frac{\gamma_2}{\eta^3} (3\theta^2 - 1) + \left[\frac{a'' \gamma_2}{(1 - e'' \cos E')^3} \right] \\
\left[3\theta^2 - 1 + 3 \sin^2 \dot{\chi}'' \cos(2g'' + 2\delta') \right] \tag{4.8} \\
e = e'' + \dot{e}'' t + \delta_1 e'' + \frac{\eta^2 \gamma_2}{2} \left\{ \frac{3\theta^2 - 1}{\eta^6} \left[\frac{e''}{1 + \eta^3} \left\{ 3 - e''^2 (3 - e''^2) \right\} \right. \right. \\
+ \left. \left. \left\{ 3 + e'' \cos \delta' \cdot (3 + e'' \cos \delta') \right\} \cos \delta' \right] + \frac{3(1 - \theta^2)}{\eta^6} \right. \\
\left. \left. \left[e'' + \left\{ 3 + e'' \cos \delta' (3 + e'' \cos \delta') \right\} \cos \delta' \right] \cos (2\delta' + 2g'') \right\} \right.
\end{aligned}$$

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD (con't)

$$- \frac{\eta^2 \gamma_2'}{2} (1 - \theta^2) \left[3 \cos(2g'' + \delta') + \cos(2g'' + 3\delta') \right] \quad (4.9)$$

$$\begin{aligned} i = i'' - \frac{e'' \theta}{\eta^2 \sin i''} & \delta_1 e + e'' \gamma_2' \theta \sin i'' \sin \delta' \sin(2\delta' + 2g'') \\ & + 2e'' \gamma_2' \theta \sin i'' \cdot \cos \delta' \cos(2\delta' + 2g'') + \frac{3}{2} \gamma_2' \theta \sin i'' \cos(2\delta' + 2g'') \end{aligned} \quad (4.10)$$

$$\begin{aligned} g + \ell = g' + \ell' + \frac{\gamma_2'}{4} & \left\{ -6\alpha(\delta' - \ell'' + e'' \sin \delta') + (3 - 5\theta^2) \right. \\ & \left. \left[3 \sin(2\delta' + 2g'') + 3e'' \sin(2g'' + \delta') + e'' \sin(2g'' + 3\delta') \right] \right\} \\ & + \frac{e'' \eta^2 \gamma_2'}{4(1 + \eta)} \left\{ 2(3\theta^2 - 1)(\sigma + 1) \sin \delta' + 3(1 - \theta^2) \right. \\ & \left. \left[(1 - \sigma) \sin(2g'' + \delta') + (\sigma + 1/3) \sin(2g'' + 3\delta') \right] \right\} \end{aligned} \quad (4.11)$$

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD (con't)

$$h = h' + \left[2e''\gamma_2'\theta \cos\delta' + \frac{3}{2}\gamma_2'\theta \right] \sin(2g'' + 2\delta') \\ - e''\gamma_2'\theta \sin\delta' \cos(2\delta' + 2g'') - 3\gamma_2'\theta (\delta' - \ell'' + e''\sin\delta') \quad (4.12)$$

and

$$e\delta\ell = \frac{1}{2} \frac{e''\eta^3}{\gamma_2'} \left\{ \frac{1}{4}\gamma_2'\beta - \frac{5}{6}\gamma_4'\gamma \right\} \sin 2g'' \\ - \left\{ \frac{1}{4} \frac{\gamma_3'}{\gamma_2'} \eta^3 \sin\lambda'' + \frac{5}{64} \frac{\gamma_5'}{\gamma_2'} \eta^3 \sin\lambda'' (4 + 9e^2'') \delta \right\} \cdot \\ \cos g'' + \frac{35}{384} \frac{\gamma_5'}{\gamma_2'} \eta^3 e^2'' \lambda \sin\lambda'' \cos 3g'' \\ - \frac{1}{4} \gamma_2' \eta^3 \left\{ 2(3\theta^2 - 1)(\sigma + 1) \sin\delta' + 3(1 - \theta^2)(1 - \sigma) \sin(2g'' + \delta') \right. \\ \left. + \left(\sigma + \frac{1}{3} \right) \sin(2g'' + 3\delta') \right\} \quad (4.13)$$

where

$$u = \left(\frac{\eta}{1 - e''\cos E'} \right)^2 + \left(\frac{1}{1 - e''\cos E'} \right) \quad (4.14)$$

4.2 PROCESSING EQUATIONS FOR THE BROUWER-LYDDANE METHOD (con't)

the eccentric anomaly E' is obtained from a Newton-Raphson iteration upon the Kepler equation

$$E' - e'' \sin E' = \ell'' \quad , \quad (4.15)$$

and the true anomaly ϕ' is found from:

$$\sin \phi' = \frac{\eta \sin E'}{1 - e'' \cos E'} \quad , \quad (4.16)$$

$$\cos \phi' = \frac{\cos E' - e''}{1 - e'' \cos E'} \quad . \quad (4.16)$$

The final osculating values for a , i , and h are computed from equations (4.8), (4.10), and (4.12), respectively. Equations (4.2), (4.9), (4.11) and (4.13) are used to calculate final osculating values for ℓ , g , and e for the following relations:

$$A = e \cos \ell'' - e \delta \ell \sin \ell'' \quad , \quad (4.17)$$

$$B = e \sin \ell'' + e \delta \ell \cos \ell'' \quad , \quad (4.18)$$

$$\ell = \tan^{-1} (B/A) \quad , \quad (4.19)$$

$$g = (\ell + g) - \ell \quad , \quad (4.20)$$

and

$$e = (A^2 + B^2)^{1/2} \quad . \quad (4.21)$$

4.3 PROCESSING EQUATIONS FOR THE KEPLERIAN UPDATE METHOD

The Keplerian update method treats a , e , and i as constants and updates ℓ , g , and h using only their secular variations. The updated elements are given by:

$$\left. \begin{aligned} a &= a'' \\ e &= e'' \\ i &= i'' \end{aligned} \right\} , \quad (4.22)$$

$$\ell = n_0 t \left[1 + \frac{3}{2} \gamma_2' \eta (3 \cos^2 i'' - 1) \right] + \ell_0'' , \quad (4.23)$$

$$g = \frac{3}{2} n_0 \gamma_2' t (5 \cos^2 i'' - 1) + g_0'' , \quad (4.24)$$

and

$$h = -3 n_0 \gamma_2' t \cos i'' + h_0'' . \quad (4.25)$$

The constants appearing in the last three equations are defined in equations (4.1).

4.4 PROCESSING EQUATIONS FOR TRANSFORMING ORBITAL ELEMENTS TO CARTESIAN COORDINATES

The SIP function uses the inertial Cartesian position and velocity vectors to compute inview periods. The inertial position and velocity are obtainable from the osculating orbital elements generated via the methods described above through application of the following transformations:

$$\vec{r} = a \begin{pmatrix} \cos E - e \\ \sqrt{1 - e^2} \sin E \end{pmatrix} , \quad (4.26)$$

4.4 PROCESSING EQUATIONS FOR TRANSFORMING ORBITAL ELEMENTS TO CARTESIAN COORDINATES

and

$$\frac{\dot{r}}{r} = \frac{(\mu a)^{\frac{1}{2}}}{a(1 - e \cos E)} \tilde{Q} \begin{pmatrix} -\sin E \\ \sqrt{1 - e^2} \cos E \end{pmatrix}, \quad (4.27)$$

where

$$\tilde{Q} = \begin{pmatrix} \cosh \cos g - \sinh \cos i \sin g & -\cosh \sin g - \sinh \cos i \cos g \\ \cos g \sinh + \cos h \cos i \sin g & \cosh \cos i \cos g - \sinh \sin g \\ \sin i \sin g & \sin i \cos g \end{pmatrix}. \quad (4.28)$$




FIGURE 5-1. Process Flow of the Brouwer Mean Element Converter

SECTION 5

THE BROUWER MEAN ELEMENT CONVERTER (BMC)

5.1 FUNCTIONAL DESCRIPTION

The primary tasks performed by the BMC are to receive post orbit adjust inertial Cartesian position and velocity vectors at t'_{OA} , i.e., $\vec{r}(t'_{OA})$ and $\dot{\vec{r}}(t'_{OA})$, and:

- (i) transform the osculating inertial Cartesian components to osculating Brouwer orbital elements;
- (ii) iteratively solve for the Brouwer mean element set associated with the osculating inertial Cartesian components.

The iterative solution mentioned in (ii) above utilizes the BRAUER subroutine of the BOG function. The process flow of the BMC function is shown in Figure 5-1.

5.2 PROCESSING EQUATIONS

The post-orbit adjust osculating inertial Cartesian vectors $\vec{r}(t'_{OA}) = (x, y, z)$ and $\dot{\vec{r}}(t'_{OA}) = (\dot{x}, \dot{y}, \dot{z})$ are transformed to osculating Brouwer orbital elements using the following relationships:

$$a = \left[\frac{2}{|\vec{r}|} - \frac{|\dot{\vec{r}}|^2}{\mu} \right]^{-1}, \quad (5.1)$$

$$e = \left\{ \frac{(\vec{r} \cdot \dot{\vec{r}})^2}{\mu a} + \left[\frac{|\vec{r}| |\dot{\vec{r}}|^2}{\mu} - 1 \right]^2 \right\}^{\frac{1}{2}}, \quad (5.2)$$

$$i = \tan^{-1} \left\{ \frac{[(y\dot{z} - z\dot{y})^2 + (z\dot{x} - x\dot{z})^2]^{\frac{1}{2}}}{x\dot{y} - y\dot{x}} \right\}, \quad (5.3)$$

5.2 PROCESSING EQUATIONS (con't)

$$\ell = \tan^{-1} \left\{ \frac{(\dot{x}\dot{y} - y\dot{x})}{x|\dot{x}\dot{y} - y\dot{x}|} \right\}, \quad (5.4)$$

$$h = \tan^{-1} \left\{ \frac{y\dot{z} - z\dot{y}}{x\dot{z} - z\dot{x}} \right\},$$

and

$$g = \tan^{-1} \left\{ \frac{z|\dot{\vec{r}} \times \dot{\vec{r}}| \left[\frac{|\dot{\vec{r}}|^2}{\mu} - 1 - e^2 \right] + [x(z\dot{x} - x\dot{z}) - y(y\dot{z} - z\dot{y})] \sqrt{1 - e^2} \frac{\dot{\vec{r}} \cdot \dot{\vec{r}}}{(\mu a)^{1/2}}}{z|\dot{\vec{r}} \times \dot{\vec{r}}| \sqrt{1 - e^2} \frac{\dot{\vec{r}} \cdot \dot{\vec{r}}}{(\mu a)^{1/2}} - [x(z\dot{x} - x\dot{z}) - y(y\dot{z} - z\dot{y})] \left[\frac{|\dot{\vec{r}}|^2}{\mu} - 1 - e^2 \right]} \right\}. \quad (5.5)$$

The iterative technique used to find the mean Brouwer elements from the associated osculating elements is similar to that described by Walter⁵. However, a nonsingular orbital element set devised by Cohen and Hubbard⁶ is used here to provide computational stability for near circular orbits. This nonsingular mean element set, represented by \bar{B}_j , where

⁵ Walter, H.G., "Conversion of Osculating Elements into Mean Elements", The Astronomical Journal, Vol. 72, No. 8, 1967, pp. 994 - 997.

⁶ Cohen, C.J. and Hubbard, E.C., "A Nonsingular Set of Orbit Elements", The Astronomical Journal, Vol. 67, No. 1, 1962, pp. 10 - 15.

5.2 PROCESSING EQUATIONS (con't)

$$\bar{\beta}_j = \begin{cases} p^{\frac{1}{2}} \cos\left(\frac{i''}{2}\right) \cos\left(\frac{h'' + g'' + \ell''}{2}\right), & j = 1 \\ p^{\frac{1}{2}} \sin\left(\frac{i''}{2}\right) \cos\left(\frac{h'' - g'' - \ell''}{2}\right), & j = 2 \\ p^{\frac{1}{2}} \sin\left(\frac{i''}{2}\right) \sin\left(\frac{h'' - g'' - \ell''}{2}\right), & j = 3 \\ p^{\frac{1}{2}} \cos\left(\frac{i''}{2}\right) \sin\left(\frac{h'' + g'' + \ell''}{2}\right), & j = 4 \\ e'' \cos \ell'' & j = 5 \\ -e'' \sin \ell'' & j = 6 \end{cases} \quad (5.6)$$

is obtained from the iterative process executed according to the scheme

$$\bar{\beta}_j^{(i+1)} = \bar{\beta}_j^{(i)} + (\beta_j^\circ - \beta_j^{(i)}) \quad , \quad j = 1, 2, \dots, 6. \quad (5.7)$$

The p in equations (5.6) is the mean semi-latus rectum. The β_j° in the last equation are the initial nonsingular osculating elements, and the $\beta_j^{(i)}$ are the osculating nonsingular elements formed using the osculating elements obtained from BRAUER on the i^{th} iteration and generated by using the Brouwer mean elements obtained from $\bar{\beta}_j^{(i)}$. This procedure is repeated on each $\bar{\beta}_j^{(i)}$ until the following convergence conditions are satisfied:

$$|\bar{\beta}_j^{(i+1)} - \bar{\beta}_j^{(i)}| < \epsilon_j \quad , \quad j = 1, 2, \dots, 6, \quad (5.8)$$

5.2 PROCESSING EQUATIONS (con't)

where the ϵ_j are small numbers. When this condition is satisfied, then

$$\bar{\beta}_j = \bar{\beta}_j^{(i+1)} \quad , \quad j = 1, 2, 3, \dots, 6, \quad (5.9)$$

and

$$p = \left(\sum_{j=1}^4 \bar{\beta}_j^2 \right)^2 \quad , \quad (5.10)$$

$$e'' = (\bar{\beta}_5^2 + \bar{\beta}_6^2)^{1/2} \quad , \quad (5.11)$$

$$a'' = p/(1 - e''^2) \quad , \quad (5.12)$$

$$i'' = 2 \tan^{-1} \left\{ \frac{(\bar{\beta}_2^2 + \bar{\beta}_3^2)^{1/2}}{(\bar{\beta}_1^2 + \bar{\beta}_4^2)^{1/2}} \right\} \quad , \quad (5.13)$$

$$\ell'' = \tan^{-1} (-\bar{\beta}_6/\bar{\beta}_5) \quad , \quad (5.14)$$

$$h'' = \tan^{-1} (\bar{\beta}_3/\bar{\beta}_2) + \tan^{-1} (\bar{\beta}_4/\bar{\beta}_1) \quad , \quad (5.15)$$

and

$$g'' = 2 \tan^{-1} (\bar{\beta}_4/\bar{\beta}_1) - (\ell'' + h'') \quad . \quad (5.16)$$

5.2 PROCESSING EQUATIONS (con't)

For completeness, the BMC function computes the Kaula semi-major axis a_k associated with the post-orbit adjust mean semi-major axis $a''(t'_{0A})$. This is generated recursively, using the Newton-Raphson method, i.e.,

$$a_k^{(i)} = g(a_k^{(i-1)}) \quad , \quad (5.17)$$

where

$$g(a_k) = a_k - \left\{ \frac{a_k^7 + 4\delta a_k^5 - \gamma a_k^4 + 4\delta^2 a_k^3 + 2\delta\gamma a_k^2 - \gamma\delta^2}{7a_k^6 + 20\delta a_k^4 - 4\gamma a_k^3 + 12\delta^2 a_k^2 + 4\delta\gamma a_k} \right\} . \quad (5.18)$$

In the last equation,

$$\delta = \frac{3J_2(1 - \frac{3}{2}\sin^2 i'')}{4(1 - e''^2)^{3/2}} \quad (5.19)$$

and

$$\gamma = (a''/a_e)^3 . \quad (5.20)$$

This iterative procedure is continued until

$$|a_k^{(i+1)} - a_k^{(i)}| < 10^{-5} . \quad (5.21)$$

DISTRIBUTION

Defense Technical Information Center
Cameron Station
Alexandria, VA 22314 (12)

Library of Congress
ATTN: Gift and Exchange Division (4)
Washington, DC 20540

National Aeronautics and Space Administration
Scientific and Technical Library
Code NHS 22, Rm. BA39
600 Independence Avenue, SW
Washington, DC 20546 (2)

Defense Mapping Agency
ATTN: Mr. Jack Calender (10)
Washington, DC 20305

Defense Mapping Agency
Hydrographic/Topographic Center
ATTN: Mr. Patrick Fell (10)
Washington, DC 20390

Defense Mapping Agency Aerospace Center
ATTN: Dr. Robert Ballew (8)
St. Louis, MO 63118

Naval Electronics Systems Command
Navy Space Project, PME106
Washington, DC 20360 (3)

Office of Chief of Naval Operations
Naval Oceanography Division (NOP-952)
Bldg. 1, U.S. Naval Observatory (2)
Washington, DC 20390

Office of Naval Operations
Navy Space Systems Division (NOP-943) (2)
Washington, DC 20350

Naval Research Laboratory
ATTN: Mr. Al Bartholomew (3)
Washington, DC 20375

Naval Oceanographic Office
Bay St. Louis, MS 39522 (2)

DISTRIBUTION (Continued)

Office of Naval Research
Physical Sciences Division
800 N. Quincy St. (2)
Arlington, VA 22217

Air Force Geophysics Laboratory
Hanscom Field
Bedford, MA 01731 (2)

Goddard Space Flight Center
ATTN: Dr. David Smith (1)
Greenbelt, MD 20771

The University of Texas at Austin
ATTN: Dr. Byron Tapley (1)
Austin, TX 78712

Applied Research Laboratory
University of Texas
ATTN: Dr. Arnold Tucker (5)
Austin, TX 78712

Physical Sciences Laboratory
New Mexico State University
Box 3 - PSL
ATTN: Dan Martin (3)
Las Cruces, NM 88003

Applied Physics Laboratory
Johns Hopkins University
Johns Hopkins Road
ATTN: Harold Black (3)
Laurel, MD 20810

Local:

E31 (GIDEP)	
E431	(10)
F14	(4)
K05	(2)
P12	(10)
K13	(20)
K14	(5)
X210	(6)

END

FILMED

9-85

DTIC